



## JOLLY ROUND 350

Small and versatile LED converter for constant current. Suitable for appliance boxes, which makes it easy to position. Excellent for minor projects such as lighting in window nooks or installation in luminaires. Dimmable via Push (230V) or 1-10V. Jolly Round has screw terminals that can manage cables up to 2.5 mm<sup>2</sup> and memory function that lights up at the previously set value after power cuts.

### DESCRIPTION

GTIN:	7392971125220
Item Name:	Jolly Round 350
Warranty:	5 years

### LIGHT TECHNICAL DATA

Life Time Driver:	50 000h/5%
Flicker (PstLM):	0,02
Stroboscopic effect (SVM):	0,004

### OPERATION AND CONNECTION


Dimmable:	Yes
Type of Dimming:	1-10V, Push 230V, Potentiometer
Driver Model:	Constant Current
Driver Type:	Built-in
Connection (type):	Screw Terminals
Connection (mm2):	2x0,5-2,5
Connection Secondary (type):	Screw Terminals
Secondary Connection (mm2):	2x0,5-1,5
Voltage Output Interval (V):	2-29V
Power Factor $\lambda$ :	0,6
Power Interval for Catalogue (W):	0-9
Max. Power (W):	9
Constant Current (mA):	350
Min. Ta (°C):	-25
Max. Ta (°C):	35
Max. Tc (°C):	80
Memory Function Power Failure:	Yes
Protection Against:	Short Circuit, Overload, Overheating 100°C

## COLOR AND MATERIAL

Material:	Plastic
Color:	White
Environmental Assessment:	Byggarubedömningen

## MEASUREMENT AND INSTALLATION

Operating Environment:	Indoor / dry locations
Installation:	Built-in
Fire Safety Marks:	MM-mark
Approval Marks:	CE
Filament Test IEC 695-2-1(°C):	850
Height (mm):	22
Diameter (mm):	57
Weight (kg):	0,041
Built-in Ø (mm):	58mm



(mm)

