



## CONVERTER PLR 350MA

Constant current converter for 350 mA or 700 mA LED light sources. For installation in appliance boxes or similar.

### DESCRIPTION

<b>GTIN:</b>	7331575109298
<b>Item Name:</b>	Converter PLR 350mA
<b>Warranty:</b>	5 years

### OPERATION AND CONNECTION

<b>Dimmable:</b>	No
<b>Type of Dimming:</b>	OnOff
<b>Driver Model:</b>	Constant Current
<b>Driver Type:</b>	Built-in
<b>Connection (type):</b>	Cable
<b>Connection (mm2):</b>	2x0,5
<b>Connection Secondary (type):</b>	Cable
<b>Secondary Connection (mm2):</b>	2x0,5
<b>Voltage Output Interval (V):</b>	2-30V
<b>Power Interval for Catalogue (W):</b>	1-10,5
<b>Constant Current (mA):</b>	350
<b>Min. Ta (°C):</b>	-10
<b>Max. Ta (°C):</b>	40
<b>Protection Against:</b>	Short Circuit, Overload, Overheating 110°C

### COLOR AND MATERIAL

<b>Material:</b>	Plastic
<b>Color:</b>	White

## MEASUREMENT AND INSTALLATION

<b>Operating Environment:</b>	Indoor / dry locations
<b>IP Degree of Protection:</b>	20
<b>Protection Class:</b>	II
<b>Fire Safety Marks:</b>	MM-mark
<b>Approval Marks:</b>	CE
<b>Height (mm):</b>	19
<b>Diameter (mm):</b>	53
<b>Weight (kg):</b>	0,05
<b>Built-in Ø (mm):</b>	53mm

