



CONVERTER IP67 LEDSTRIP 230V DIM 3M

Converter for LEDstrip 230V DIM with built-in fuse for safe operation. Fuse 5x20 2A (2-pack) is used in the IP20 converter as a replacement or spare fuse to protect the equipment in the event of an overload.

Light Technical Data

Technical data

Operation and Connection

Color and material

Measurement and installation

The converter is available in IP20 and IP67. The IP20 version must be installed in an IP-rated junction box, features a replaceable fuse, and can be placed up to 15 m from the LED strip. In the kits, the IP67 version is integrated onto the connection cable, 0.5 m from the LED strip. The separate IP67 Converter accessory instead features a 2 m cable between the LED strip and converter, as well as 1 m to the mains plug.

Controls

DESCRIPTION

GTIN:	7392971156798
Item Name:	Converter IP67 LEDstrip 230V DIM 3m
Warranty:	5 years

LIGHT TECHNICAL DATA

Life Time Driver:	50 000h/5%
-------------------	------------

TECHNICAL DATA

Voltage (type):	DC
Voltage Interval (V):	220...240V
Voltage Nominal (V):	230

OPERATION AND CONNECTION

Driver Model:	Constant Voltage
Driver Type:	Stand Alone
Driver Manufacturer:	Hide-a-lite
Connection (type):	Cable
Length Connection (cm):	300
Connection (mm2):	2x1,0
Length Connection Secondary (cm):	50
Secondary Connection (mm2):	2x0,75
Min. Ta (°C):	-25
Max. Ta (°C):	40
Operating Temperature:	-25...+40°C
Max. Tc (°C):	90

COLOR AND MATERIAL

Material:	Plastic
Color:	White

MEASUREMENT AND INSTALLATION

Operating Environment:	Outdoor
Installation:	Surface mounted
Approval Marks:	CE
Length (mm):	3000
Width (mm):	37
Height (mm):	37
Weight (kg):	0,25

